





# LED WALL PACK LIGHT BG001C SERIES COLOR/POWER SELECTABLE

## DIMENSIONS


### BG001C ▼




20W/24W




30W/42W



lampstand 30W/42W



60W/80W



100W/120W





## LED Wall Pack light Parameter table-DLC Premium

Item description	LEDBG20W001C	LEDBG24W001C	LEDBG30W001C-D/MG	LEDBG42W001C-D/MG	LEDBG60W001C-D/MG	LEDBG80W001C-D/MG	LEDBG100W001C-D/MG	LEDBG120W001C-D/MG
Dimensions [mm]	209*134*122(L*W*H)		257*140*160(L*W*H)		320*190*253(L*W*H)		400*205*268(L*W*H)	
Input voltage [VAC]	100-277VAC							
Input frequency [HZ]	50/60							
Input current(max) [A]	0.2	0.24	0.3	0.42	0.6	0.8	1.0	1.2
Input wattage [W]	20±5%	24±5%	30±5%	42±5%	60±5%	80±5%	100±5%	120±5%
Power factor	>0.9		>0.95		≥0.95@220V			
Luminous flux@3000K [Lm]	2600	3120	3900	5460	7800	10400	13000	15600
Colour temperature [K]	3000K/4000K/5000K							
Colour rendering index [Ra]	≥80							
Average life [h]	> 54000							
Net weight [Kg]	1.65/ (set)	1.65/ (set)	2.46/ (set)	2.46/ (set)	5.2/set	5.3/set	7.3/set	
Gross weight [Kg]	2.1/ (set)	2.1/ (set)	3.1/ (set)	3.1/ (set)	6.0/set	6.1/set	8.1/set	
Work environment	Wet Location							
LED chip(2835)	64		112		240		336	
Ambient Temperature [°C]	-25°-45°							

## INSTALLATION

### BG001C INSTALLATION 1 20W-42W Surface mounting1

COLOR/POWER SELECTABLE




1. Take off the plate A from the luminaire and fix the plate A on the surface of the building with screws.
2. Connect the luminaire to the plate A with hook, then connect to supply source.
3. Fix the luminaire to the plate A at part B. 4. Fix the luminaire with screws at the bottom.

# LED WALL PACK LIGHT BG001C SERIES COLOR/POWER SELECTABLE

## BG001C INSTALLATION 2


60W-120W Surface mounting 2



1. Remove the screws and open the fixture, then disconnect the supply source and grounded wires, then take off the spring buckle on the one side of the chain at the bottom.
2. Remove part A from the fixture, and punch the mounting hole on part A.
3. Fasten part A to the wall and connect the supply source.
4. Join part A to the fixture through the holes on the fixture.

## BG001C INSTALLATION 3

60W-120W Surface mounting 1



1. Take off the plate A from the luminaire and fix the plate A on the surface of the building with screws.
2. Connect the luminaire to the plate A with hook, then connect to supply source.
3. Fix the luminaire to the plate A at part B.
4. Fix the luminaire with screws at the bottom.